




Brusatori
MOTORI ELETTRICI

Via Meucci, 7
20012 Cuggiono (Milano) ITALY
☎ 0039 02 25068401
Fax 0039 02 25060140
http:// www.brusatori.eu - e-mail:
info@brusatori.eu




BR SERVOMOTORS WHIT ENCODER EnDat


POWER



POWER WITH BRAKE



SIGNAL



CONNETTOR VIEW FROM WELDING SIDE

POWER

Connector motor	Connector Interconnectron	Connector AXV 10P
A	1	U
B	2	V
C	3	W
D	⊥	GND
	A	PT
	B	PT
(E)	C	(BRAKE +24V)
(F)	D	(BRAKE 0V)

ENCODER ASSOLUTO: EQN 1325 EnDat (312 213-14)
ECN 413 EnDat (317 944-10)
EQN 425 EnDat (605 381-15)

Connettor motor 19P	Data sheet encoder absolute EQN 1325 EnDat			
A	GND	8 bianco/verde		
B	GND			
C	CLOCK	4 viola		
D	CLOCK-	9 giallo		
E	DATA	12 grigio		
F	DATA-	1 rosa		
G				
H	B	7 blu/nero		
J	B-	6 rosso/nero		
K	A-	10 giallo/nero		
L	A	3 verde/nero		
M				
N				
P	+Vcc	2 marrone/verde		
R				
S	PT			
T	PT			
U	Up Sensor	11 blu		
V	0V Sensor	5 bianco		